



Trusted by Professionals Since 1989



BioCentrix C6 Fingerprint Reader



C6 is an optical fingerprint reader with built-in card reading module. C6 captures and stores fingerprint images to use as templates to verify each specific finger's unique ridge pattern. All fingerprint templates can be downloaded and uploaded to the template management software via TCP/IP configuration. C6 is compatible with all ELID access controllers to provide a complete access management system.

PRODUCTS FEATURES:


- Storage capacity: 3,000 fingerprint templates, 3,000 cards and 3,000 passwords
- Built-in card reader module (EM/MIFARE, depending on the type of card reader used)
- Multiple verification mode: fingerprint, password, card
- Fast verification time
- Large colour LCD display
- Intuitive operation and installation
- WIFI Enabled (For specific models only)
- Fingerprint templates can be downloaded and uploaded via TCP/IP
- Fingerprint templates/cards/passwords can be edited directly on the device
- Compatible with all ELID access controllers

SPECIFICATIONS

| |
|--|
| Fingerprint Capacity: 3,000 |
| Card Capacity: 3,000 |
| Password Capacity: 3,000 |
| Fingerprint Verification: 1:1, 1:N |
| Working Mode: Online/Offline |
| Verification Mode: Fingerprint, ID Card, Password, FP+Card, PIN+Card, FP+PIN+Card |
| Verification Time: < 1 second |
| False Rejection Rate: < 0.01% |
| False Acceptance Rate: < 0.0001% |
| Fingerprint Sensor: Optical Sensor, 500dpi |
| Screen: 3 inches (Colour LCD Display) |

| |
|---|
| Display Language: English |
| Communication (Template Management): TCP/IP, USB Disk |
| Communication (Access Controller): Wiegand-26/ Wiegand-34 |
| Working Humidity: 20%-60% |
| Working Temperature: 0°C - 50°C |
| Power Supply : 12VDC |
| Idle Current : 400mA |
| Working Current : 500mA |
| Sound Indicator : Buzzer, Voice |
| Battery Back-up : No |
| Dimension : 86 x 86 x 30mm |

CONFIGURATION



ORDERING INFORMATION

| | |
|------------------|---|
| SBERC6E01 | BioCentrix C6 Fingerprint Reader with EM Module |
| SBERC6EW1 | BioCentrix C6 Fingerprint Reader with EM Module, WIFI support |
| SBERC6M01 | BioCentrix C6 Fingerprint Reader with Mifare Module |
| SBERC6U01 | BioCentrix C6 USB Fingerprint Reader (enrolment device) |



For more information: Check out the website at www.elid.com, or contact our dealers. ELID has a policy of continuous research and development, and reserves the right to change specifications without notice.

www.elid.com